Amendments to the Claims:

1	1. (canceled)
1	2. (canceled)
1	3. (canceled)
1	4. (canceled)
l	5. (currently amended) A coaxial feedthrough connector for connecting an RF signal
2	through a wall in a hazardous environment, the connector comprising:
3	(a) a base having an axial passage defined by a passage interior surface, A
4	connector in accordance with claim 4 wherein the base having has a threaded
5	boss extending from the base and coaxially with the passage for connecting
б	the base to the wall or to a conduit connected to the wall;
7	(b) a coaxial transmission line extending through the passage;
8	(c) a nonconductive sealing compound filling at least a longitudinal segment of
9	the passage and sealingly engaged to both the transmission line and to the
10	passage surface; and
11	(d) a coaxial connector mounted in an end of the passage for connection to a
12	coaxial cable, the coaxial connector being electrically connected to the
13	transmission line.

Page 2 of 6

- 6. (original) A connector in accordance with claim 5 wherein a radome is mounted on the 1
- base opposite the boss and an antenna radiating element is mounted within the radome 2
- and is electrically connected to the transmission line. 3
- 7. (canceled) 1
- 8. (previously presented) A coaxial feedthrough connector for connecting an RF signal 1
- through a wall in a hazardous environment, the connector comprising: 2
- (a) a base having an axial passage defined by a passage interior surface, the base 3
- comprising an outer base member and a coaxial insert mounted in a coaxial bore 4
- formed in the outer base member, the coaxial insert having a central passage 5
- coaxial with a central passage in the outer base member, the central passages 6
- 7 being contiguous and together forming said axial passage;
- (b) a coaxial transmission line extending through the passage; and 8
- (c) a nonconductive sealing compound filling at least a longitudinal segment of the 9
- passage and sealingly engaged to both the transmission line and to the passage 10
- surface 11
- wherein the central passage of the outer base member is smaller than the central 12
- passage of the insert and a coaxial cable connector is engaged in the end of the 13
- smaller central passage, and wherein the sealing compound extends into sealing 14
- contact with the coaxial cable connector. 15

Page 3 of 6

- 9. (original) A connector in accordance with claim 8 wherein an interior, annular 1
- shoulder is formed in the insert adjacent the central passage of the outer base member for 2
- increased sealant sealing area between the insert and the outer base member. 3
- 10. (original) A connector in accordance with claim 9 wherein the base has a threaded 1
- boss extending from the base and coaxially with the passage for connecting the base to 2
- the wall or to a conduit connected to the wall. 3
- 11. (original) A connector in accordance with claim 10 wherein a radome is mounted on 1
- the base opposite the boss and an antenna radiating element is mounted within the 2
- radome and is electrically connected to the transmission line. 3
- 12. (original) A connector in accordance with claim 11 wherein the sealing compound is 1
- 2 a silicone sealing compound.
- 13. (original) A connector in accordance with claim 12 wherein the silicone sealing 1
- 2 compound is a two part, GE-RTV-627 compound.
- 14. (previously presented) A coaxial feedthrough connector for connecting an RF signal 1
- through a wall in a hazardous environment, the connector comprising: 2
- (a) a base having an axial passage defined by a passage interior surface; 3
- (b) a coaxial transmission line extending through the passage; and 4

Page 4 of 6

PAGE 4/7 * RCVD AT 10/28/2005 8:15:02 AM [Eastern Daylight Time] * SVR:USPTO-EFXRF-6/24 * DNIS:2738300 * CSID:614 575 2149 * DURATION (mm-ss):02-04

- (c) a nonconductive sealing compound filling at least a longitudinal segment of the 5 passage and sealingly engaged to both the transmission line and to the passage 6 7 surface,
- wherein a coaxial boss is formed at each opposite end of the base, a coaxial cable 8 connector is mounted in the boss at each end of the passage and each coaxial 9 connector is electrically connected to an opposite end of the transmission line and in 10 sealing contact with the sealing compound. 11
- 15. (original) A connector in accordance with claim 14 wherein the sealing compound is 1
- 2 a silicone sealing compound.
- 16. (original) A connector in accordance with claim 15 wherein the silicone sealing 1
- compound is a two part, GE-RTV-627 compound. 2

Page 5 of 6